

*30 MHz to 3 GHz, general purpose*  
**3 AXIS RADIO FREQUENCY  
ELECTROMAGNETIC  
FIELD METER**

**Model : EMF-819**

*ISO-9001, CE, IEC1010*



**Lutron**

**LUTRON ELECTRONIC**

*The Art of Measurement*

**30 MHz to 3 GHz, general purpose  
Radio Frequency Radiation Meters Electromagnetic Field strength measurement**

# 3 AXIS RF ELECTROMAGNETIC FIELD METER

**Model : EMF-819**

**FEATURES**

* 3 Axis probe.
* Radio frequency electromagnetic field tester.
* Wide measuring frequency ranges, 30 MHz to 3 GHz.
* EMF-819 is used for broadband devices of monitoring the wide range radio frequency electromagnetic field value.
* For precision measurement consideration, the meter is included one probe : EP-05H ( High frequency Probe, 100 MHz to 3 GHz )
* Unit : V/m, W/m <sup>2</sup> , mW/cm <sup>2</sup> .
* Frequency team selection : two points, Normal, 2.45 GHz.
* Alarm setting function can warn the user if the measuring antenna is too near the strong radiation sources, the buzzer will sound to remind the user.
* Peak hold function to latch peak value.
* Data hold function to lock the current reading.
* RS232 computer interface.
* Hard carrying case is included.
* Large size LCD with contrast adjustment, which can fit best viewing angle.
* Microcomputer circuit provides special function & offers high accuracy.
* Powered by 006P DC 9V battery or DC 9V adapter.

**APPLICATIONS**

This meter is specially developed for measuring or monitoring electromagnetic field, for example:  
cell-phone station, hospital equipment, radar , micro-wave oven, radiation work, TV antenna , Radio station , welding equipment , baking- equipment, television , computer , factory, laboratory , and other environment...etc.

**SAFETY INSTRUCTIONS**

<b><i>Danger</i></b>								
* For worker's safety, be aware that persons with electromagnetic implant ( e.g. cardiac-pacemaker ) are subject to especial danger in some case.								
* Particular to observe the local safety regulations of the operator of the equipment.								
* Before using the device, it need to know that how to setting " alarm-limit " value.								
<b><i>Attention</i></b>								
* Claims by some scientists that long term exposure to electromagnetic field may be the cause of childhood leukemia & other forms of cancer.								
* Complete answers to any of these and related questions are not currently available. At the present time the most common practice is to avoid excess exposure over long period of time.								
* Complete answers to any of these and related " Prudent Avoidance " as stated by the Environmental Protection Agency(EPA) USA is recommended.								
* According to ICNIRP of reference levels to time-varying electromagnetic fields,The E-field strength levels are:								
<b>General public</b>								
<table border="1"> <tr><th>Frequency range</th><th>e-field strength (V/m)</th></tr> <tr><td>10 to 400 MHz</td><td>28</td></tr> <tr><td>400 to 2000 MHz</td><td>1.375 x f<sup>1/2</sup></td></tr> <tr><td>2 to 300 GHz</td><td>61</td></tr> </table>	Frequency range	e-field strength (V/m)	10 to 400 MHz	28	400 to 2000 MHz	1.375 x f <sup>1/2</sup>	2 to 300 GHz	61
Frequency range	e-field strength (V/m)							
10 to 400 MHz	28							
400 to 2000 MHz	1.375 x f <sup>1/2</sup>							
2 to 300 GHz	61							
<b>Occupational</b>								
<table border="1"> <tr><th>Frequency range</th><th>e-field strength (V/m)</th></tr> <tr><td>10 to 400 MHz</td><td>61</td></tr> <tr><td>400 to 2000 MHz</td><td>3 x f<sup>1/2</sup></td></tr> <tr><td>2 to 300 GHz</td><td>137</td></tr> </table>	Frequency range	e-field strength (V/m)	10 to 400 MHz	61	400 to 2000 MHz	3 x f <sup>1/2</sup>	2 to 300 GHz	137
Frequency range	e-field strength (V/m)							
10 to 400 MHz	61							
400 to 2000 MHz	3 x f <sup>1/2</sup>							
2 to 300 GHz	137							

**GENERAL SPECIFICATIONS**

Circuit	Custom one-chip of microprocessor LSI circuit.
Display	LCD size : 58 mm x 34 mm.
Measurement Unit	V/m, mW/cm <sup>2</sup> , W/m <sup>2</sup> .
Accuracy	< 2 dB.
Probe structure	3 Axis.
Probe Input Impedance	50 OHM
Sensor Structure	Semiconductor
Frequency Team Selection	Two points selection : Normal, 2.45 GHz.
Data Hold	Freeze the display reading.
REC Function	Record Maximum & Minimum value.
Power off	Auto shut off saves battery life or manual off by push button. * Can default auto power off or manual power off. * When default auto power off , power will off automatically after 10 min. if no button be pressed.
Peak Hold	To latch the peak measurement value.
Alarm Setting	Buzzer will sound when display over the setting value.
Sampling Time	Approx. 1 second.
Low Battery Indicator	When display show Low battery Indicator, it should change the batteries.
Data Output	RS 232 PC serial interface.
Operating Temperature	0 to 50 °C.
Operating Humidity	Less than 80 %RH.
Power Supply	DC 9 V battery ( 006P ) * Heavy duty or Alkaline type. DC 9V adapter input.
Power Current	Approx. DC 5.95 mA
Weight	425 g/ 0.94 LB.
Dimension	Main instrument : 200.0 x 76.2 x 36.8 mm Probe : 70 mm ( diameter) x 240 mm ( length)
Accessories Included	Instruction manual..... 1 PC EP-05H Probe.....1 PC Memory card for EP-05H..... 1 PC Hard carrying case.....1 PC DC 9V power adapter.....1 PC
Optional Accessories	RS232 cable, UPCB-02. USB cable, USB-01. Data Acquisition software,SW-U801-WIN.

**ELECTRICAL SPECIFICATIONS ( 23 ± 5 °C )**

Strength Range	Resolution	Effective Value
0 to 200.00 V/m	0.01 V/m	> 1 V/m
0 to 99.999 W/m <sup>2</sup>	0.001 W/m <sup>2</sup>	> 0.03 W/m <sup>2</sup>
0 to 9.9999 mW/cm <sup>2</sup>	0.0001 mW/cm <sup>2</sup>	> 0.0003 mW/cm <sup>2</sup>
Frequency Range	Accuracy	Test Point
30 MHz to 3 GHz	< 2 dB *	60 V/m

**Remark:**

\* **Measurement under other frequency range ( below 100 MHz and over 2.5 GHz ), the reading value just for reference only.**

\* **For precision measurement consideration, it should select the " Frequency Team point " near the frequency value of measuring object.**